# $\textbf{Centraverse}^{\text{\tiny{TM}}}~\textbf{CVG}~\textbf{Gooseneck}~\textbf{Microphones}$

#### **Overview**

Professional gooseneck electret condenser microphone for use in general installed sound reinforcement applications. Designed with dual gooseneck sections for full articulation, the CVG12 and CVG18 provide scalable, best-in-class performance in a wide variety of locations, including podiums and desktops.

### **Specifications**

Cartridge Type         Electret Condenser           Frequency Response         70–16000 Hz           Polar Pattern         Cardioid           Output Impedance         180 Ω           Sensitivity (at 1 kHz, open circuit voltage)         -33 dBV/Pa[1] (22 mV)           Maximum SPL (1 kHz at 1% THD)         120 dB SPL
Polar Pattern         Cardioid           Output Impedance         180 Ω           Sensitivity (at 1 kHz , open circuit voltage)         -33 dBV/Pa[1] (22 mV)
Output Impedance         180 Ω           Sensitivity (at 1 kHz , open circuit voltage)         -33 dBV/Pa[1] (22 mV)
Sensitivity (at 1 kHz , open circuit voltage)  -33 dBV/Pa[1] (22 mV)
Maximum SPL (1 kHz at 1% THD)         120 dB SPL
Signal to Noise Ratio 67 dB (referenced at 94 dB SPL)
Dynamic Range 93 dB
Self Noise (equivalent SPL, A-weighted, typical) 27 dB SPL
Common Mode Rejection (10 Hz to 100 kHz) >45 dB
Preamplifier Output Clipping Level (1% THD) -7 dBV
<b>Polarity</b> Positive pressure on diaphragm produces positive voltage on pin 2 with respect to
Power Requirements         11–52 V DC[4], 2.0 mA
Environmental Requirements  Operating Temperature Range: -18° C to 57° C (0° F to 135° F) Relative Humidity: 0 to 95%

## **Available Models**

CVG12-B/C	12" Gooseneck Condenser Microphone, Inline Pre-Amp, Cardioid, Black
CVG18-B/C	18" Gooseneck Condenser Microphone, Inline Pre-Amp, Cardioid, Black
CVG12S-B/C	12" Gooseneck Condenser Microphone, Inline Pre-Amp, Mute Switch, LED, Cardioid, Black
CVG18S-B/C	18" Gooseneck Condenser Microphone, Inline Pre-Amp, Mute Switch, LED, Cardioid, Black
CVG12RS-B/C	12" Gooseneck Condenser Microphone, Inline Pre-Amp, Mute Switch, Light-Ring, Cardioid, Black
CVG18RS-B/C	18" Gooseneck Condenser Microphone, Inline Pre-Amp, Mute Switch, Light-Ring, Cardioid, Black


#### **Furnished Accessories**

95A16670	Windscreen
RPM640	Mounting Flange

## **Optional Accessories**

•	
CVD-B	Desktop Base
ACVG4WS-B	Replacement Windscreens (4-pack)
A57F	Microphone Clip
C25J	25' XLR Cable
A400SM	Shock Mount

#### CVG Polar Pattern



#### CVG Frequency Response

