Confidea CHT

Confidea Charging Tray



Description

The Confidea Charging Tray is a rackmountable 3 U high container that can recharge 6 Confidea Battery Packs at once.

It has an auto-ranging power supply and a loop-through mains connector. A maximum of 4 chargers can be daisychained for 110 VAC regions and 8 for 220 VAC regions. It is designed for multiple mounting possibilities, having 19" rack, wall or table mounting capabilities.

Battery packs can be fully charged in 4 hours or quick charged to reach 50% capacity in 1 hour.

Features

- » Loop-through mains connector
- » 6 slots for 1 Confidea Battery Pack each
- » 19" rack mountable

Certification

Region	Certification
Europe	CE



Specifications

Mechanical	
Material	PC/ABS 1 mm steel
Color	RAL 9011
Size (mm)	130 (w) × 480 (h) × 140 (d)
Size packed (mm)	255 (w) × 540 (h) × 265 (d)
Weight	3920g
Weight packed	4860g
Electrical	
Supply voltage	100-230 VAC ±10%
Output power	200 W
Supply voltage	100-230 VAC ±10%
Environment	
Operating temperature	-10 to 60 °C

All information copyright Televic Conference, 2018. Televic reserves the right to change this document without notice. Version 1.0, 20 July, 2018 Leo Bekaertlaan 1 8870 Izegem, België

+32 51 30 30 45 conference@televic.com www.televic-conference.com